





Verdrahtungsplan für sks 2-D Bus System (VX2203) für maximal 48 WE

Beim Prüfen der Anlagenverdrahtung ist es sehr wichtig, das an den Verteilerklemmstellen geringe Übergangswiderstände entstehen, daß heißt, entweder Verlöten oder eine selbstnachstellende Klemme Typ Wago verwenden. Unter keinen Umständen ist eine Verdrahtung mit LSA PLUS Leisten wegen der geringen Spannung der Anlagen vorzunehmen. Der maximale Leitungswiderstand darf den Wert von 7.5 Ohm nicht überschreiten.

Art.942 BEISPIEL CODE TABELLE

Dezimal	DIP - Schalter						
Nr.	1	2	3	4	5	6	7
A	1ON	OFF	OFF	OFF	OFF	OFF	OFF
A	2OFF	ON	OFF	OFF	OFF	OFF	OFF
A	3ON	ON	OFF	OFF	OFF	OFF	OFF
A	4OFF	OFF	ON	OFF	OFF	OFF	OFF
A	5ON	OFF	ON	OFF	OFF	OFF	OFF
A	6OFF	ON	ON	OFF	OFF	OFF	OFF
A	7ON	ON	ON	OFF	OFF	OFF	OFF
A	8OFF	OFF	OFF	ON	OFF	OFF	OFF
A	9ON	OFF	OFF	ON	OFF	OFF	OFF
A	10OFF	ON	OFF	ON	OFF	OFF	OFF
A	11ON	ON	OFF	ON	OFF	OFF	OFF
A	12OFF	OFF	ON	ON	OFF	OFF	OFF

weitere Haustelegone



- DIP-Schalter Sw1 - Funktionen der Schalterstellungen.
- (1) - muss immer auf on stehen.
 - (2) - auf off ist die Gesprächszeit 1 Minuten (Voreingestellt 1 Minute)
 - (3) - auf on ist die Gesprächszeit 2 Minuten
 - (3) - nicht verstellen muss immer auf off stehen.
 - (4) - auf off ist die Türöffnerzeit 2 Sek.
 - (4) - oder auf on ist die Türöffnerzeit 4 Sekunden(Voreingestellt 2 Sek.)

Art.942 CODE TABELLE

Dezimal Nr.	DIP-Schalter Nr.							I
	1	2	3	4	5	6	7	
A	1	ON	OFF	OFF	OFF	OFF	OFF	OFF
A	2	OFF	ON	OFF	OFF	OFF	OFF	OFF
A	3	ON	ON	OFF	OFF	OFF	OFF	OFF
A	4	OFF	OFF	ON	OFF	OFF	OFF	OFF
A	5	ON	OFF	ON	OFF	OFF	OFF	OFF
A	6	OFF	ON	ON	OFF	OFF	OFF	OFF
A	7	ON	ON	ON	OFF	OFF	OFF	OFF
A	8	OFF	OFF	OFF	ON	OFF	OFF	OFF
A	9	ON	OFF	OFF	ON	OFF	OFF	OFF
A	10	OFF	ON	OFF	ON	OFF	OFF	OFF
A	11	ON	ON	OFF	ON	OFF	OFF	OFF
A	12	OFF	OFF	ON	ON	OFF	OFF	OFF
B	1	ON	OFF	ON	ON	OFF	OFF	OFF
B	2	OFF	ON	ON	ON	OFF	OFF	OFF
B	3	ON	ON	ON	ON	OFF	OFF	OFF
B	4	OFF	OFF	OFF	OFF	ON	OFF	OFF
B	5	ON	OFF	OFF	OFF	ON	OFF	OFF
B	6	OFF	ON	OFF	OFF	ON	OFF	OFF
B	7	ON	ON	OFF	OFF	ON	OFF	OFF
B	8	OFF	OFF	ON	OFF	ON	OFF	OFF
B	9	ON	OFF	ON	OFF	ON	OFF	OFF
B	10	OFF	ON	ON	OFF	ON	OFF	OFF
B	11	ON	ON	ON	OFF	ON	OFF	OFF
B	12	OFF	OFF	OFF	ON	ON	OFF	OFF
C	1	ON	OFF	OFF	ON	ON	OFF	OFF
C	2	OFF	ON	OFF	ON	ON	OFF	OFF
C	3	ON	ON	OFF	ON	ON	OFF	OFF
C	4	OFF	OFF	ON	ON	ON	OFF	OFF
C	5	ON	OFF	ON	ON	ON	OFF	OFF
C	6	OFF	ON	ON	ON	ON	OFF	OFF
C	7	ON	ON	ON	ON	ON	OFF	OFF
C	8	OFF	OFF	OFF	OFF	OFF	ON	OFF
C	9	ON	OFF	OFF	OFF	OFF	ON	OFF
C	10	OFF	ON	OFF	OFF	OFF	ON	OFF
C	11	ON	ON	OFF	OFF	OFF	ON	OFF
C	12	OFF	OFF	ON	OFF	OFF	ON	OFF
D	1	ON	OFF	ON	OFF	OFF	ON	OFF
D	2	OFF	ON	ON	OFF	OFF	ON	OFF
D	3	ON	ON	ON	OFF	OFF	ON	OFF
D	4	OFF	OFF	OFF	ON	OFF	ON	OFF
D	5	ON	OFF	OFF	ON	OFF	ON	OFF
D	6	OFF	ON	OFF	ON	OFF	ON	OFF
D	7	ON	ON	OFF	ON	OFF	ON	OFF
D	8	OFF	OFF	ON	ON	OFF	ON	OFF
D	9	ON	OFF	ON	ON	OFF	ON	OFF
D	10	OFF	ON	ON	ON	OFF	ON	OFF
D	11	ON	ON	ON	ON	OFF	ON	OFF
D	12	OFF	OFF	OFF	OFF	ON	ON	OFF